Notation

For graphs used in class:

V is a set of consecutive integers starting at 0.

E.g., $V = \{0, 1, 2\}$.

Integers sometimes expressed in radix-k form.

Let i, k, and a be positive integers.

Then notation $i_{(a)}$ indicates digit a in i's radix-k representation.

Digit 0 is the least significant.

Digit notation can be juxtaposed: $i = i_{(n-1)}i_{(n-2)}\cdots i_{(0)}$,

where n is the number of radix-k digits in i.

Examples:

Let $i = 1234_{10} = 4d2_{16} = 3412_7$.

For $k = 16$, $i = i_{(2)}i_{(1)}i_{(0)} = 4d2$ and so $i_{(2)} = 4$, $i_{(1)} = \mathtt{d}$, $i_{(0)} = 2$.

For $k = 7$, $i = i_{(3)}i_{(2)}i_{(1)}i_{(0)} = 3412$ and so $i_{(3)} = 3$, $i_{(2)} = 4$, $i_{(1)} = 1$, $i_{(0)} = 2$.

03-3

Direct Network Graph Representation

Idea: describe (specify) direct network using graph.

Network ⇔ Graph

Links ⇔ Edges

Nodes ⇔ Vertices

Graph Representation

Uses two sets:

- Set of vertices, V.
- Set of edges E.

Usual notation, $G = (V, E)$:

- G is the name of the graph.
- V is the set of vertices.
- E is the set of edges.

03-1

Other Useful Notation

$\langle x \rangle \equiv \{0, 1, \ldots, x-1\}$.

E.g., $\langle 4 \rangle \equiv \{0, 1, 2, 3\}$.

03-4

Consider $G = (V, E)$.

Let $u \in V$ and $v \in V$.

The following two statements are equivalent:

- There is an edge between u and v.
- $(u, v) \in E$.

For any graph (V, E): $E \subseteq V \times V$.

03-2

Usefulness

Diameter and average distance too large for general use.

Bisection width too small for general use.

Might be useful for special-purpose applications.

Useful for simple classroom examples.

03-7

k-ary n-cube (KNC) /n-D Mesh Network Families

Popular direct network families.

n-D mesh is generalization of a 2-D mesh.

k-ary n-cube is n-D mesh with *wraparound* connections.

Properties

- All members are easily routed.
- Members exhibit medium to high diameter.
- Suitable for many parallel algorithms.

Plan

- Special Cases Described
- Families Described

03-5

Two-Dimensional Mesh Network

Generalization of linear network to two dimensions.

Graph description of k^2-node 2-dimensional mesh:

$$V = \left\langle k^2 \right\rangle = \{0, 1, \ldots, k^2 - 1\}$$

$$E = \{\, (i, i+1) \mid i \in \left\langle k^2 \right\rangle,\ (i \bmod k) < k - 1 \,\} \cup \{\, (i, i+k) \mid i \in \left\langle k^2 - k \right\rangle \,\}$$

03-8

Linear Network

Nodes arranged in a line.

Graph description of N-node linear network:

$$V = \langle N \rangle = \{0, 1, \ldots, N-1\}$$

$$E = \{\, (i, i+1) \mid i \in \langle N - 1 \rangle \,\}$$

Properties

Degree, $\delta = 2$.

Routing: increment (or decrement) vertex of current position until at destination.

Distance, $d_{u,v} = |u - v|$.

Diameter, $D = N - 1$.

Average Distance:

$$\overline{d} = \frac{2}{N(N-1)} \sum_{i=0}^{N-2} \sum_{j=i+1}^{N-1} j - i = \frac{N+1}{3}.$$

Bisection width, 1.

03-6

n-D Mesh: Generalization of previous two networks to n dimensions.

Graph description:

$V = \langle k^n \rangle$.

$E = \{ (u, u + k^i) \mid i \in \langle n \rangle , \ u \in V, \ u_{(i)} < k - 1 \}$.

Mesh Routing:

- Treat vertex as n-digit, radix-k number.
- Choose a digit.
- Increment (or decrement) this digit of the vertex of the current position until equal to the corresponding digit of destination vertex.
- Repeat until all digits are chosen.

Properties

Degree, $\delta = 4$.

Routing:

- Treat vertex as 2-digit, radix-k number.
- Increment (or decrement) least-significant digit of vertex of current position until equal to least-significant digit of destination vertex.
- Increment (or decrement) most-significant digit of vertex of current position until equal to most-significant digit of destination vertex.

Distance, $d_{u,v} = \left| u_{(0)} - v_{(0)} \right| + \left| u_{(1)} - v_{(1)} \right|$.

Diameter, $D = 2(k - 1)$.

Average Distance:

$$\overline{d} = \frac{2 \ k \ (k + 1) \, (k - 1)}{3 \ (k^2 - 1)}.$$

Bisection width, k.

Usefulness

Diameter large, but acceptable.

May be easy to build.

Used in general-purpose computers.

Well suited to some algorithms.

Works poorly with other algorithms.

Choice of k and n for Mesh

Goal: determine tradeoffs when k and n varied.

Method:

- *Fix* some measures.
- *Vary* k and n.
- *Observe* effect on other measures.

Case 1: Fix N.

Observe effect on average distance, latency, bisection width, and cost.

Case 2: Fix N and Bisection Width

Observe effect on average distance, latency, and cost.

Case 3: Fix N and Cost

Observe effect on average distance, latency, and bisection width.

EE 7725 Lecture Transparency. Formatted 13:04, 10 September 1997 from lsli03.

03-15

Mesh Properties

Degree:

$$\delta = \begin{cases} 2n, & \text{if } k > 2; \\ n, & \text{if } k = 2. \end{cases}$$

Distance, $d_{u,v} = \sum_{i=0}^{n-1} \left| u_{(i)} - v_{(i)} \right|$.

Diameter, $D = n(k-1)$.

Average Distance:

$$\overline{d} = \frac{n}{3} \frac{(k-1)(k+1)k^{n-1}}{(k^n - 1)} \approx \frac{n}{3} \left(k - \frac{1}{k} \right).$$

Bisection width, k^{n-1}.

EE 7725 Lecture Transparency. Formatted 13:04, 10 September 1997 from lsli03.

03-13

Equations for All Cases

Cost (For These Comparisons).

Count number of links, include width:

$$\mathrm{C} = \frac{1}{2} N \delta w.$$

Number of Nodes

$N = k^n$ by definition.

$\Rightarrow n = \log_k N$

$\Rightarrow k = N^{\frac{1}{n}}$

Latency (For These Comparisons)

$$L = \overline{d} + \frac{M}{w} - 1$$

EE 7725 Lecture Transparency. Formatted 13:04, 10 September 1997 from lsli03.

03-16

Usefulness For $k = 2$.

Short (logarithmic) average distance and diameter.

Easy to route.

Large degree (bad).

EE 7725 Lecture Transparency. Formatted 13:04, 10 September 1997 from lsli03.

03-14

k-ary n-cube Properties

Degree (same as mesh):

$$\delta = \begin{cases} 2n, & \text{if } k > 2; \\ n, & \text{if } k = 2. \end{cases}$$

Distance, $d_{u,v} = \sum_{i=0}^{n-1} \min\left\{ \left|u_{(i)} - v_{(i)}\right|, k - \left|u_{(i)} - v_{(i)}\right| \right\}$.

Diameter, $D = n \left\lfloor \frac{k}{2} \right\rfloor$.

Average Distance, $\overline{d} = \begin{cases} \frac{n}{4} \frac{k^{n+1}}{k^n - 1} & \text{if } k \text{ even} \\ \frac{n}{4} \frac{k^{n+1} + k^{n-1}}{k^n - 1} & \text{if } k \text{ odd} \end{cases}$.

$$\approx \frac{nk}{4}$$

Bisection width, $\begin{cases} k^{n-1}, & \text{if } k = 2; \\ 2k^{n-1}, & \text{if } k > 2 \end{cases}$.

k-ary n-cube: Mesh with Wraparound Connections

Graph description of k^n-node k-ary n-cube:

$$V = \langle k^n \rangle.$$

$$E = \{ (u, u + k^i) \mid i \in \langle n \rangle, u \in V, u_{(i)} < k - 1 \} \cup \{ (u, u - (k-1)k^i) \mid i \in \langle n \rangle, u \in V, u_{(i)} = k - 1 \}.$$

Moore Bound

Motivation: does the hypercube have a minimum diameter?

Can use Moore bound to answer this.

Method Outline:

- Fix degree and diameter of minimum-diameter network.

  (Degree of δ, diameter of d).

- Find maximum number of nodes that any such network could have.
- Solve for diameter.

k-ary n-cube Routing (similar to mesh):

- Treat vertex as n-digit, radix-k number.
- Choose a digit.
- Increment (or decrement) this digit of the vertex of the current position until equal to the corresponding digit of destination vertex.
- Repeat until all digits are chosen.

If $\delta \gg 1$:

$d \approx \log_\delta N$.

Note that this is much better than the KNC family.

But do such networks exist?

03-23

Shuffle and Shift Functions

Used to describe edges in several graphs.

Idea: Rotate digits in a number (with an end-around shift).

Two definitions will be given:

Shuffle Function (for Integers)

Let $u \in \langle mk \rangle$ where m and k are positive integers.

The shuffle function $\sigma_{m,k} \mid \langle mk \rangle \rightarrow \langle mk \rangle$ is given by:

$$\sigma_{m,k}(u) \equiv mu + \left\lfloor \frac{u}{k} \right\rfloor \pmod{mk}.$$

Examples:

$\sigma_{2,4}(1) = 2$

$\sigma_{2,4}(0) = 0$

$\sigma_{2,4}(5) = 3$

03-24

Derivation

Call some node the *center* of the network.

Let $N'(i)$ denote the number of nodes at distance i from center.

Then:

$N'(0) = 1$

$N'(1) \leq \delta$

$N'(2) \leq \delta(\delta - 1) = N'(1)(\delta - 1)$

$N'(3) \leq \delta(\delta - 1)^2 = N'(2)(\delta - 1)$

$N'(i) \leq N'(i-1)(\delta - 1) = \delta(\delta - 1)^{(i-1)}$ for $i > 1$.

03-21

Let N denote the total number of nodes in a network of diameter d and degree δ.

$$\begin{aligned} N &= \sum_{i=0}^{d} N'(i) \\ &\leq N'(0) + N'(1) + \sum_{i=2}^{d} N'(i) \\ &\leq 1 + \delta + \delta \sum_{i=2}^{d} (\delta - 1)^{i-1} \\ &\leq 1 + \delta + \delta \sum_{j=1}^{d-1} (\delta - 1)^{j} \\ &\leq 1 + \delta + \delta \left(\frac{(\delta - 1)^d - (\delta - 1)}{(\delta - 1) - 1} \right) \\ &\leq \frac{\delta(\delta - 1)^d - 2}{\delta - 2} \end{aligned}$$

Solving for d yields:

$$d \geq \log_{(\delta - 2)} \left(\frac{N(\delta - 2) + 2}{\delta} \right).$$

03-22

The Exchange Function

Used to describe edges in several graphs.

Idea: change least-significant-digit of a number.

Exchange function for Integers

Let $u \in \langle mk \rangle$ and $i \in \langle m \rangle$, where m and k are positive integers.

Then the exchange function $\chi \mid \langle mk \rangle, \langle m \rangle \rightarrow \langle mk \rangle$ is given by

$$\chi_m(u,i) = m \left\lfloor \frac{u}{m} \right\rfloor + i$$

Examples:

$\chi_2(5,0) = 4$

$\chi_3(13,2) = 14$

EE 7725 Lecture Transparency. Formatted 13:04, 10 September 1997 from lsli03.

03-27

Exchange function for Sequences

Let $u_{(n-1)}\, u_{(n-2)} \ldots u_{(0)}$ be any sequence of symbols, where $u_{(i)} \in S$,

and $\mathcal{S}$ be the set of all possible sequences.

Then the exchange function $\chi \mid \mathcal{S}, S \rightarrow \mathcal{S}$ is given by:

$\chi(u_{(n-1)}\, u_{(n-2)} \ldots u_{(0)}, x) = u_{(n-1)}\, u_{(n-2)} \ldots x$, where $x \in S$.

Examples:

$\chi(abc, d) = abd$

$\chi(1011, 0) = 1010$

$\chi(\heartsuit\clubsuit\diamondsuit, \spadesuit) = \heartsuit\clubsuit\spadesuit$

EE 7725 Lecture Transparency. Formatted 13:04, 10 September 1997 from lsli03.

03-28

Shift Functions (for Sequences)

Let $u_{(n-1)}\, u_{(n-2)} \ldots u_{(0)}$ be any sequence of symbols, where $u_{(i)} \in S$,

and $\mathcal{S}$ be the set of all possible sequences.

Then the left-shift function $\sigma_{\mathrm{l}} \mid \mathcal{S} \rightarrow \mathcal{S}$ is given by:

$$\sigma_{\mathrm{l}}\left(u_{(n-1)}\, u_{(n-2)} \ldots u_{(0)}\right) = u_{(n-2)}\, u_{(n-3)} \ldots u_{(0)}\, u_{(n-1)}.$$

Examples:

$\sigma_{\mathrm{l}}(abc) = bca$

$\sigma_{\mathrm{l}}(1101) = 1011$

The right-shift function $\sigma_{\mathrm{r}} \mid \mathcal{S} \rightarrow \mathcal{S}$ is given by:

$$\sigma_{\mathrm{r}}\left(u_{(n-1)}\, u_{(n-2)} \ldots u_{(0)}\right) = u_{(0)}\, u_{(n-1)} \ldots u_{(2)}\, u_{(1)}.$$

Examples:

$\sigma_{\mathrm{r}}(abc) = cab$

$\sigma_{\mathrm{r}}(1101) = 1110$

EE 7725 Lecture Transparency. Formatted 13:04, 10 September 1997 from lsli03.

03-25

Relationship Between Shuffle and Shift Functions

The shuffle function is a special case of the shift functions.

- Given any set of symbols S,
- any positive integer n,
- and any set of sequences $\mathcal{S} = S \times S \times \cdots \times S$ (n times),
- and any $S \in \mathcal{S}$,

there exist a corresponding:

- set of digits $\langle |S| \rangle$,
- set of integers $\langle |S|^n \rangle$,
- a mapping $\mathcal{S} \rightarrow \langle |S|^n \rangle$

such that for any $S_1 \in \mathcal{S}$ if $\sigma_{\mathrm{l}}(S_1) = S_2$ and $\sigma_{\mathrm{r}}(S_1) = S_3$ then $\sigma_{|S|,|S|^{n-1}}(s_1) = s_2$ and $\sigma_{|S|^{n-1},|S|}(s_1) = s_3$

where s_1, s_2, and s_3 are the integers corresponding to S_1, S_2, and S_3, respectively.

In other words, any sequence of symbols could be viewed as a sequence of digits.

EE 7725 Lecture Transparency. Formatted 13:04, 10 September 1997 from lsli03.

03-26

Non-minimal Routing of Shuffle Exchange Graph

For request $(u_{(n-1)}u_{(n-2)}\cdots u_{(0)},\ v_{(n-1)}v_{(n-2)}\cdots v_{(0)})$:

- Step 0:

  "Replace" least-significant-digit of source with MSD of destination.

  $(u_{(n-1)}u_{(n-2)}\cdots u_{(0)},\ u_{(n-1)}u_{(n-2)}\cdots v_{(n-1)})$.

- Step $i \in \{1, 2, \ldots, n-1\}$:

  Left shift the current node number.

$$\begin{aligned}&(u_{(n-i)}u_{(n-i-1)}\cdots u_{(1)}v_{(n-1)}\cdots v_{(n-i)},\\ &\quad u_{(n-i-1)}u_{(n-i-2)}\cdots u_{(1)}v_{(n-1)}\cdots u_{(n-i)})\end{aligned}$$

  "Replace" digit $n-i$ of source with digit $n-i-1$ of destination.

  Take edge

$$\begin{aligned}&(u_{(n-i-1)}u_{(n-i-2)}\cdots u_{(1)}v_{(n-1)}\cdots u_{(n-i)},\\ &\quad u_{(n-i-1)}u_{(n-i-2)}\cdots u_{(1)}v_{(n-1)}\cdots v_{(n-i-1)})\end{aligned}$$

EE 7725 Lecture Transparency. Formatted 13:04, 10 September 1997 from lsli03.
03-31

Shuffle-Exchange Graph

Let m and n be positive integers.

The m,n shuffle-exchange, (V, E) graph is given by:

$V = \langle m^n \rangle$

$E = \{\, (u, \sigma_{m,m^n-1}(u)) \mid u \in V \,\} \cup \{\, (u, \chi_m(u,i)) \mid u \in V,\ i \in \langle m \rangle \,\}$.

EE 7725 Lecture Transparency. Formatted 13:04, 10 September 1997 from lsli03.
03-29

de Bruijn Graph

Also called Good graph.

Let m and n be positive integers.

The m,n de Bruijn Graph, (V, E) is given by:

$V = \langle m^n \rangle$

$E = \{\, (u, \chi_m(\sigma_{m,m^n-1}(u), i)) \mid u \in V\ i \in \langle m \rangle \,\}$.

EE 7725 Lecture Transparency. Formatted 13:04, 10 September 1997 from lsli03.
03-32

Shuffle-Exchange Graph Characteristics:

Degree: $\delta = m + 1$.

Distance: $d_{u,v} \leq 2n - 1$.

The exact distance cannot be expressed in compact form.

Diameter: $D = 2n - 1$.

For example, $d_{0,m^n-1} = 2n - 1$.

Average distance: not known, probably close to diameter.

Bisection width: for $m = 2$: $BW = \Theta(2^{n-1})$.

EE 7725 Lecture Transparency. Formatted 13:04, 10 September 1997 from lsli03.
03-30

de Bruijn Graph Characteristics:

Degree: $\delta = 2m$.

Distance: $d_{u,v} \leq n$.

The exact distance cannot be expressed in a compact form.

Diameter: $D = n$.

For example, $d_{0,m^n-1} = n$.

Average distance:

$$\overline{d} \geq \begin{cases} n - 3 - \frac{9}{8}, & \text{if } m = 2; \\ n - 1 - \frac{8}{9}, & \text{if } m = 3; \\ n - 1 - \frac{25}{72}, & \text{if } m = 4; \\ n - \frac{2(m+1)^2}{m(m-1)^2}, & \text{if } m > 4. \end{cases}$$

Non-minimal Routing of the de Bruijn Graph

For request $(u_{(n-1)}u_{(n-2)}\cdots u_{(0)},\ v_{(n-1)}v_{(n-2)}\cdots v_{(0)})$:

- Step $i \in \{0, 1, \ldots, n-1\}$:

  Left-shift the current node number, then exchange LSD.

$$\begin{aligned} &(u_{(n-i-1)}u_{(n-i-2)}\cdots u_{(0)}v_{(n-1)}\cdots v_{(n-i)}, \\ &\ u_{(n-i-2)}u_{(n-i-3)}\cdots u_{(0)}v_{(n-1)}\cdots v_{(n-i-1)}) \end{aligned}$$